

MX3 USB



:: Product Description

- * 9 inputs on 4 channels (3line, 3phonos,1mic, 2USB)
- * 2 Bidirectional USB connections (play and record at the same time!)
- * 1 separate DJ mic with talk-over
- * 1 Master output + 1 record output
- * Easy replaceable crossfader
- * High quality, easy gliding 'steel rail' DJ faders
- * LED VU-meters
- * Pre-fade listening with cue mix option

:: Technical Information

Power Supply: AC 9V / 1A

Frequency response: 20-20.000Hz (+/-2dB)

THD + noise: S/N Ratio (IHF-A): >87dB @ 1kHz.

USB connections: USB 2.0, bidirectional (44,1kHz / 16bit)

Windows & MacOS compatible.

USB cable (not included): Lmax = 3m

Mic inputs: 3,16mV @ 2,2kΩ

Line/CD inputs: 320mV @ 50kΩ

Phono inputs: 3,16mV @ 47kΩ

Record output: 775mV @ 1kΩ

Master output: 1.68V @ 1k Ω ; unbal.

Talkover: 0dB \rightarrow -14dB

Channel tone controls: +12dB / -26dB (70Hz, 1kHz, 13kHz)

DJ Mic tone controls: +10dB / -10dB (100Hz, 10kHz)

Headphone: 1,12V @ 32 Ω ;

Dimensions: 254(W) x 308(D) x 82,5(H) mm

Weight: 3,4kg